

**B R O A D W A V E T E C H N O L O G I E S I N C .**

**MODEL 852 - 879 - FM1  
IMPEDANCE MATCHING PAD**

**Frequency Range:** DC - 1000 MHz

**Impedance:** 75 Ohms nominal ( Male side )  
50 Ohms nominal ( Female side )

**Insertion Loss:** 5.7 dB nominal

**VSWR:** 1.40:1 maximum

**Input Power:** 1 Watt average

**Connectors:** Type F Male / N Female

**Outline Drawing:** MED - 0456

ECF #	Date	Rev.
Issue	2/22/05	0

**Approved By:** \_\_\_\_\_