

B R O A D W A V E T E C H N O L O G I E S I N C .

**MODEL 879 - 854 - MF1
IMPEDANCE MATCHING PAD**

Frequency Range: DC - 1000 MHz

Impedance: 75 Ohms nominal (male side)
50 Ohms nominal (female side)

Insertion Loss: 5.7 dB nominal

VSWR: 1.40:1 maximum

Input Power: 1 Watt average

Connectors: Type F Male / BNC Female

Outline Drawing: MED - 0302

ECF #	Date	Rev.
Issue	12/2/04	0

Approved By: _____